





# Phase Adjuster -Adapter type- **NEW**

## ► Overview

Coaxial adapter with 9 psec. phase adjusting feature.

## ► Product

<b>02X0654-00 : 2.92mmK Phase Adjuster (P-J)</b>	
	
<b>02X0655-00 : 1.85mmV Phase Adjuster (P-J)</b>	
	

## ► Feature

- The best way to adjust skew in final tuning
- Small adapter type, perfect to use in narrow space

## ► Application

- Final skew adjustment in differential signal
- Skew tuning in any application

## ► Specification

Item#	02X0654-00		02X0655-00	
Connector	2.92mmK/J-P		1.85mmV/J-P	
Frequency Range	DC ~ 40GHz		DC ~ 65GHz	
Impedance	50 $\Omega$			
V.S.W.R.	DC ~ 20GHz	20 ~ 40GHz	DC ~ 40GHz	40 ~ 65GHz
	1.3	1.45	1.2	1.35
Insertion Loss (in Max.)	0.7dB (DC ~ 40GHz)		0.85dB (DC ~ 65GHz)	
Delay Time (mechanical length)	9ps (2.7mm)		9ps (2.8mm)	
Operating Temperature	0°C ~ 60°C			