

SMPM-2.4mm ADAPTERS











► Overview

Adapter for SMPM connector and 2.4mm connector. As a new product, we have developed this adapter with our knowledge and experience of millimeter wave. The product has excellent V.S.W.R. and insertion loss. The electric lengths for these series are unified

► Applications

High frequency measurement, Connections of high speed data-communication devices, optical component, and millimeter wave device and modules.

► Product

Product : 02R0322-00		ADP SMPM/P-2.4mm/P										
		<table border="1"> <tr> <td>V.S.W.R.</td> <td>DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4</td> </tr> </table>	V.S.W.R.	DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4								
V.S.W.R.	DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4											
		<table border="1"> <thead> <tr> <th>Connector</th> <th>Material</th> <th>Plating</th> </tr> </thead> <tbody> <tr> <td>SMPM/P</td> <td>SUS</td> <td>Pv</td> </tr> <tr> <td>2.4mm/P</td> <td>SUS</td> <td>Pv</td> </tr> </tbody> </table>	Connector	Material	Plating	SMPM/P	SUS	Pv	2.4mm/P	SUS	Pv	
Connector	Material	Plating										
SMPM/P	SUS	Pv										
2.4mm/P	SUS	Pv										
Product : 02R0321-00		ADP SMPM/P-2.4mm/J										
		<table border="1"> <tr> <td>V.S.W.R.</td> <td>DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4</td> </tr> </table>	V.S.W.R.	DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4								
V.S.W.R.	DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4											
		<table border="1"> <thead> <tr> <th>Connector</th> <th>Material</th> <th>Plating</th> </tr> </thead> <tbody> <tr> <td>SMPM/P</td> <td>SUS</td> <td>Pv</td> </tr> <tr> <td>2.4mm/J</td> <td>SUS</td> <td>Pv</td> </tr> </tbody> </table>	Connector	Material	Plating	SMPM/P	SUS	Pv	2.4mm/J	SUS	Pv	
Connector	Material	Plating										
SMPM/P	SUS	Pv										
2.4mm/J	SUS	Pv										
Product : 02R0323-00		ADP SMPM/J-2.4mm/P										
		<table border="1"> <tr> <td>V.S.W.R.</td> <td>DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4</td> </tr> </table>	V.S.W.R.	DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4								
V.S.W.R.	DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4											
		<table border="1"> <thead> <tr> <th>Connector</th> <th>Material</th> <th>Plating</th> </tr> </thead> <tbody> <tr> <td>SMPM/J</td> <td>BeCu</td> <td>Au</td> </tr> <tr> <td>2.4mm/P</td> <td>SUS</td> <td>Pv</td> </tr> </tbody> </table>	Connector	Material	Plating	SMPM/J	BeCu	Au	2.4mm/P	SUS	Pv	
Connector	Material	Plating										
SMPM/J	BeCu	Au										
2.4mm/P	SUS	Pv										
Product : 02R0324-00		ADP SMPM/J-2.4mm/J										
		<table border="1"> <tr> <td>V.S.W.R.</td> <td>DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4</td> </tr> </table>	V.S.W.R.	DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4								
V.S.W.R.	DC ~ 26.5GHz ≤ 1.25 26.5 ~ 50GHz ≤ 1.4											
		<table border="1"> <thead> <tr> <th>Connector</th> <th>Material</th> <th>Plating</th> </tr> </thead> <tbody> <tr> <td>SMPM/J</td> <td>BeCu</td> <td>Au</td> </tr> <tr> <td>2.4mm/J</td> <td>SUS</td> <td>Pv</td> </tr> </tbody> </table>	Connector	Material	Plating	SMPM/J	BeCu	Au	2.4mm/J	SUS	Pv	
Connector	Material	Plating										
SMPM/J	BeCu	Au										
2.4mm/J	SUS	Pv										